

Operation manual

LED Flush mount light

Models:

62-961, 62-962, 62-963, 62-964

With integrated dimmable driver



Thank you for purchasing our product. This fixture has been manufactured from components with advanced optoelectronics to ensure high reliability and long life. Before assembling please read this Operation Manual carefully and save in a safe place for future reference. Please note that all electrical connections must be in accordance with local and National Electrical Code standards as well as local building codes. In case you are not familiar with proper wiring connections and building codes, consult a qualified electrician.

Safety recommendations

1. RISK OF ELECTRIC SHOCK – THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH APPLICABLE INSTALLATION CODES BY A PERSON FAMILIAR WITH MENTIONED ABOVE CODES AND HAZARDS INVOLVED. DISCONNECT POWER AT CIRCUIT BREAKER OR FUSE BEFORE INSTALLING OR SERVICING.
2. Before use of the product carefully read the whole Operation Manual.
3. THE PRODUCT IS PURPOSED FOR INTERIOR USE ONLY, SUITABLE FOR DAMP LOCATIONS.
4. Protect the product against direct contact with water.
5. Assemble the product only with the use of parts provided and the housing; improper assembly may result in device failing which could damage the product, personal property or cause injury.
6. Assembly shall follow with accessories delivered with the set only.
7. The device is not a toy, KEEP OUT OF REACH OF CHILDREN.

Specifications:

Models: 62-961, 62-962, 62-963, 62-964

Power consumption: 13.5W

Color Temp.: 2700K/3000K/4000K/5000K

Life span: 40,000h

**Illumination authorization <5%
per 10,000h**




As an ENERGY STAR partner, Satco has determined that this product meets the ENERGY STAR® guidelines for energy efficiency

Installation A — Hard wire




Step 1

For junction box installation, disconnect power at circuit breaker.



Step 2

Mount the bracket to junction box using 2 screws (provided).



Step 3

Connect AC cable (Neutral and Hot wire) from electrical box to socket adapter, using wire nuts (provided).

Installation B — Screw in



For application with keyless socket preinstalled, simply screw base (from fixture) to ceiling socket. Mounting bracket and socket adapter are not used.




✓
Installed.
Congratulations...
enjoy the light!



Step 4

Screw socket adapter to base on fixture.



Step 5

Align the spring clips from fixture with holes in bracket and press up to snap into place.



✓
Installed. Congratulations...
enjoy the light!

Dimming

This product is compatible with most residential type dimmers available on the market. The dimming performance will depend on kind of dimmer and dimmer settings. Visit Satco.com for an up to date list of compatible dimmers.

Cleaning

- Clean with a soft or damp cloth. While cleaning with the damp cloth make sure the power is off.
- Do not clean with liquids or abrasives.

5 Year limited warranty

The purchased product is covered with a 5 year warranty in respect of any defect in material or workmanship after purchase date.

Satco shall bear no responsibility on account of guarantee, as well as shall bear no liability for any faults, in case of improper operation, use negligence, accident or exposure to natural hazard, or excessive use over the limits specified for the unit, or if any unauthorized alteration or repair followed.